


2000 WATT LPG DUAL FUEL INVERTER

82001i-E-DF 82001i-E-DF-EU

Max AC output:	2000/1800 (LPG)
Noise Level:	53 dBA @ 7m
Running Watts:	1600/1440 (LPG)
Warranty:	3 years
Certification:	CE Approved, EU Stage V



i DESCRIPTION

The Champion Power Equipment 100402 2000-Watt Dual Fuel Portable Inverter Generator is ideal for camping, powering items around the Caravan or providing backup for a few basics. This unit is not recommended for emergency home backup.

The innovative EZ Start Dial takes the confusion out of starting an engine, plus it allows you to switch fuels with a quick turn of the dial. Cold Start Technology ensures a quick start in cold weather.

The easy to read Digital LED Display includes maintenance, low oil and receptacle status indicators and monitors power output, total run time, fuel level and fuel life. Champion minimizes the hassle of refuelling in the dark with Fuel Fill Assist LED, a cleverly designed push-button LED built right into the handle to illuminate the gasoline fill area.

MEGAPHONE FEATURES

- 2000 Max Watts
- 1600 Running Watts
- Propane Gas or Petrol Powered
- Super quiet at only 53 dBA
- 12v DC Outlet
- True sine wave inverter technology
- Overload protection
- Electric Push Button Start
- Intelligent 3in1 Volt Meter
- Parallel Connectable with optional ParaLINK kit
- Runs up to 11 hours on 25% load (petrol)
- Includes dual port USB adapter.
- Smart Economy Mode

SHIELD SPECIFICATIONS

Starting Watts	2235 / 2011 LPG
Max Watts	2000 / 1800 LPG
Rated Watts	1600 / 1440 LPG
AC Load	2 x 240v 13 Amp (UK) 2 x 220v 16 Amp (EU)
Frequency	50Hz
Engine	80cc Champion OHV
Fuel Capacity	4.1 Litres
Oil Capacity	0.37 Litres
Noise Level	53 dBA @ 7m
Start Type	Manual
RPM	Auto based on load
Dimensions (L*W*H)	52 x 32 x 43 cm
Certification	CE, EU Stage V Approved
Weight (Kg)	21.5
Operation capacity (hr)	11 Hrs @ 25% load (Petrol)

+ INCLUDED

- Oil Funnel
- Dual USB Adapter
- Propane Gas Pipe